



GASOLINE POWER SUITCASE PORTABLE GENERATOR 2000 WATT

Product Features and Benefits:

The new Axmen Power Portable Digital Inverter Generator Provides 2000 Watt Max / 1600 Watt Rated AC output and is powered by DJ148F, 100cc, OHV Engine with recoil method start engine is a great addition to your camping as well as a cost effective and convenient solution for power outages or other emergency situations.

The AX2000i has the following features and benefits:

This powerful 2000 Watt max / 1600 Watt rated output portable inverter generator offers extremely clean AC power and extends runtime with high efficiency inverter design. Powered by a 100 cc OHV gasoline engine with low oil shutdown. The 1 gallon fuel tank provides a run time of 6 hours at 50% average rated load. This model features 120V AC output with recoil start engine.

- ❖ Eco mode provides outstanding fuel efficiency.
- ❖ Overload protection.
- ❖ 12v DC output.
- ❖ Operation with 59dB sound rating.
- ❖ 1 Year warranty.

Model	AX2000i
Engine Brand and Model	DJ148D OHV
Engine HP and Displacement	7 HP / 100 cc
Engine Starting Method	Recoil Starting
Engine Warranty	1 Year
Max AC Output	2000 Watt
Rated AC Output	1600 Watt
Voltages	120 VAC
Outlets	(1) 5-20 Duplex
Frequency	60 Hertz
Run Time (50% Load)	6 Hours
Tank Size	1 Gallon
Sound Rating (Decibels)	54~59 dB
Shipping Weight	60 lbs
Dimensions (L x W x H)	20 x 11 x 17 in.

